

S1 S2 for communication between the indoor and outdoor unit. Use 18/2 stranded, shielded wire. Ground the 18/2 wires ground wire at any green screw only at either the indoor or outdoor unit do not ground these wires at both pieces of equipment. Cut back the ground wire and electrical tape the end that isn't grounded.

L1 L2 power in. Either hot wire can connect to either L1 or L2 terminal connect ground wire to



(1)L1 (2)L2 and ground . Connect the 14/4 wires to these terminals and match the same wire color with the same terminal on both the indoor and outdoor unit. You will not use the 4th wire. We recommend Black on (1)L1 Red on (2)L2 and green for ground

